

PRACTICAL STABILITY OF POSITIVE FRACTIONAL DISCRETE-TIME LINEAR SYSTEMS

Tadeusz Kaczorek

Faculty of Electrical Engineering
Białystok Technical University
Wiejska 45D, 15-351 Białystok, Poland
kaczorek@isep.pw.edu.pl

ABSTRACT

A new concept (notion) of the practical stability of positive fractional discrete-time linear systems is introduced. Necessary and sufficient conditions for the practical stability of the positive fractional systems are established. It is shown that the positive fractional systems are practically unstable if corresponding standard positive fractional systems are asymptotically unstable.

Keywords: practical stability, fractional, positive, discrete-time

1. INTRODUCTION

In positive systems inputs, state variables and outputs take only non-negative values. Examples of positive systems are industrial processes involving chemical reactors, heat exchangers and distillation columns, storage systems, compartmental systems, water and atmospheric pollution models. A variety of models having positive linear behavior can be found in engineering, management science, economics, social sciences, biology and medicine, etc.

Positive linear systems are defined on cones and not on linear spaces. Therefore, the theory of positive systems is more complicated and less advanced. An overview of state of the art in positive systems theory is given in the monographs (Farina and Rinaldi 2000; Kaczorek 2002). Mathematical fundamentals of fractional calculus are given in the monographs (Miller and Ross 1993; Nishimoto 1984; Oldham and Spanier 1974; Podlubny 1999). The fractional positive linear continuous-time and discrete-time systems have been addressed in (Kaczorek 2008b, 2007a; Ostalczyk 2000; Vinagre and Feliu 2002; Ortigueira 1997). Stability of positive 1D and 2D systems has been addressed in (Kaczorek 2007c, 2008e, 2008f; Twardy 2007a, 2007b) and the stability of positive and fractional linear systems has been investigated in (Busłowicz 2007, 2008). The reachability and controllability to zero of positive fractional linear systems have been considered in (Kaczorek 2008a, 2007a; Klamka 2002). The fractional order controllers have been developed in (Oustalup 1993). A generalization of the Kalman filter for fractional order systems has

been proposed in Sierociuk and Dzieliński 2006). Fractional polynomials and nD systems have been investigated in (Gałkowski and Kummert 2005). The notion of standard and positive 2D fractional linear systems has been introduced in (Kaczorek 2008c, 2008d).

In this paper a new concept of the practical stability of positive fractional discrete-time linear systems will be introduced and necessary and sufficient conditions for the practical stability will be established.

The paper is organized as follows.

In section 2 the basic definitions and necessary and sufficient conditions for the positivity and asymptotic stability of the linear discrete-time systems are introduced. In section 3 the positive fractional linear discrete-time systems are introduced. The main results of the paper are given in section 4, where the concept of practical stability of the positive fractional systems is proposed and necessary and sufficient conditions for the practical stability are established. Concluding remarks are given in section 5.

To the best author's knowledge the practical stability of the positive fractional systems has not been considered yet.

The following notation will be used in the paper. The set of real $n \times m$ matrices with nonnegative entries will be denoted by $R_+^{n \times m}$ and $R_+^n = R_+^{n \times 1}$. A matrix $A = [a_{ij}] \in R_+^{n \times m}$ (a vector) will be called strictly positive and denoted by $A > 0$ if $a_{ij} > 0$ for $i = 1, \dots, n$, $j = 1, \dots, m$. The set of nonnegative integers will be denoted by Z_+ .

2. POSITIVE 1D SYSTEMS

Consider the linear discrete-time system:

$$x_{i+1} = Ax_i + Bu_i, \quad i \in Z_+ \quad (1a)$$

$$y_i = Cx_i + Du_i \quad (1b)$$

where, $x_i \in R^n$, $u_i \in R^m$, $y_i \in R^p$ are the state, input and output vectors and, $A \in R^{n \times n}$, $B \in R^{n \times m}$, $C \in R^{p \times n}$, $D \in R^{p \times m}$.

Definition 1.

The system (1) is called (internally) positive if $x_i \in R_+^n, y_i \in R_+^p, i \in Z_+$ for any $x_0 \in R_+^n$ and every $u_i \in R_+^m, i \in Z_+$.

Theorem 1 (Farina and Rinaldi 2000, Kaczorek 2002).

The system (1) is positive if and only if

$$A \in R_+^{n \times n}, B \in R_+^{n \times m}, C \in R_+^{p \times n}, D \in R_+^{p \times m}. \quad (2)$$

The positive system (1) is called asymptotically stable if the solution

$$x_i = A^i x_0 \quad (3)$$

of the equation

$$x_{i+1} = Ax_i, \quad A \in R_+^{n \times n}, \quad i \in Z_+ \quad (4)$$

satisfies the condition

$$\lim_{i \rightarrow \infty} x_i = 0 \quad \text{for every } x_0 \in R_+^n \quad (5)$$

Theorem 2 (Farina and Rinaldi 2000, Kaczorek 2007c).

For the positive system (4) the following statements are equivalent:

- 1) The system is asymptotically stable
- 2) Eigenvalues z_1, z_2, \dots, z_n of the matrix A have moduli less 1, i.e. $|z_k| < 1$ for $k = 1, \dots, n$
- 3) $\det[zI_n - A] \neq 0$ for $|z| \geq 1$
- 4) $\rho(A) < 1$ where $\rho(A)$ is the spectral radius defined by $\rho(A) = \max_{1 \leq k \leq n} \{|z_k|\}$ of the matrix A
- 5) All coefficients $\hat{a}_i, i = 0, 1, \dots, n-1$ of the characteristic polynomial

$$p_{\hat{A}}(z) = \det[I_n z - \hat{A}] = z^n + \hat{a}_{n-1} z^{n-1} + \dots + \hat{a}_1 z + \hat{a}_0 \quad (6)$$

of the matrix $\hat{A} = A - I_n$ are positive.

- 6) All principal minors of the matrix

$$\bar{A} = I_n - A = \begin{bmatrix} \bar{a}_{11} & \bar{a}_{12} & \dots & \bar{a}_{1n} \\ \bar{a}_{21} & \bar{a}_{22} & \dots & \bar{a}_{2n} \\ \vdots & \vdots & \ddots & \vdots \\ \bar{a}_{n1} & \bar{a}_{n2} & \dots & \bar{a}_{nn} \end{bmatrix} \quad (7a)$$

are positive, i.e.

$$|\bar{a}_{11}| > 0, \begin{vmatrix} \bar{a}_{11} & \bar{a}_{12} \\ \bar{a}_{21} & \bar{a}_{22} \end{vmatrix} > 0, \dots, \det \bar{A} > 0 \quad (7b)$$

- 7) There exists a strictly positive vector $\bar{x} > 0$ such that

$$[A - I_n] \bar{x} < 0 \quad (8)$$

Theorem 3 (Kaczorek 2002). The positive system (4) is unstable if at least one diagonal entry of the matrix A is greater than 1.

3. POSITIVE FRACTIONAL SYSTEMS

In this paper the following definition of the fractional discrete derivative

$$\Delta^\alpha x_k = \sum_{j=0}^k (-1)^j \binom{\alpha}{j} x_{k-j}, \quad 0 < \alpha < 1 \quad (9)$$

will be used for where $\alpha \in R$ is the order of the fractional difference, and

$$\binom{\alpha}{j} = \begin{cases} 1 & \text{for } j = 0 \\ \frac{\alpha(\alpha-1)\dots(\alpha-j+1)}{j!} & \text{for } j = 1, 2, \dots \end{cases} \quad (10)$$

Consider the fractional discrete linear system, described by the state-space equations

$$\Delta^\alpha x_{k+1} = Ax_k + Bu_k, \quad k \in Z_+ \quad (11a)$$

$$y_k = Cx_k + Du_k \quad (11b)$$

where $x_k \in \mathfrak{R}^n$, $u_k \in \mathfrak{R}^m$, $y_k \in \mathfrak{R}^p$ are the state, input and output vectors and $A \in \mathfrak{R}^{n \times n}$, $B \in \mathfrak{R}^{n \times m}$, $C \in \mathfrak{R}^{p \times n}$, $D \in \mathfrak{R}^{p \times m}$.

Using the definition (9) we may write the equations (11) in the form

$$x_{k+1} + \sum_{j=1}^{k+1} (-1)^j \binom{\alpha}{j} x_{k-j+1} = Ax_k + Bu_k, \quad k \in Z_+ \quad (12a)$$

$$y_k = Cx_k + Du_k \quad (12b)$$

Definition 2. The system (12) is called the (internally) positive fractional system if and only if $x_k \in \mathfrak{R}_+^n$ and $y_k \in \mathfrak{R}_+^p$, $k \in Z_+$ for any initial conditions $x_0 \in \mathfrak{R}_+^n$ and all input sequences $u_k \in \mathfrak{R}_+^m$, $k \in Z_+$.

Theorem 4. The solution of equation (12a) is given by

$$x_k = \Phi_k x_0 + \sum_{i=0}^{k-1} \Phi_{k-i-1} B u_i \quad (13)$$

where Φ_k is determined by the equation

$$\Phi_{k+1} = (A + I_n \alpha) \Phi_k + \sum_{i=2}^{k+1} (-1)^{i+1} \binom{\alpha}{i} \Phi_{k-i+1} \quad (14)$$

with $\Phi_0 = I_n$.

The proof is given in (Kaczorek 2007a).

Lemma 1 (Kaczorek 2007a). If

$$0 < \alpha \leq 1 \quad (15)$$

then

$$(-1)^{i+1} \binom{\alpha}{i} > 0 \quad \text{for } i = 1, 2, \dots \quad (16)$$

Theorem 5 (Kaczorek 2007a). Let $0 < \alpha < 1$. Then the fractional system (12) is positive if and only if

$$A + I_n \alpha \in \mathfrak{R}_+^{n \times n}, \quad B \in \mathfrak{R}_+^{n \times m}, \quad C \in \mathfrak{R}_+^{p \times n}, \quad D \in \mathfrak{R}_+^{p \times m} \quad (17)$$

4. PRACTICAL STABILITY

From (10) and (16) it follows that the coefficients

$$c_j = c_j(\alpha) = (-1)^j \binom{\alpha}{j+1}, \quad j = 1, 2, \dots \quad (18)$$

strongly decrease for increasing j and they are positive for $0 < \alpha < 1$. In practical problems it is assumed that j is bounded by some natural number h .

In this case the equation (12a) takes the form

$$x_{k+1} = A_\alpha x_k + \sum_{j=1}^h c_j x_{k-j} + B u_k, \quad k \in Z_+ \quad (19)$$

where

$$A_\alpha = A + I_n \alpha \quad (20)$$

Note that the equations (19) and (12b) describe a linear discrete-time system with h delays in state.

Definition 3. The positive fractional system (12) is called practically stable if and only if the system (19), (12b) is asymptotically stable.

Defining the new state vector

$$\tilde{x}_k = \begin{bmatrix} x_k \\ x_{k-1} \\ \vdots \\ x_{k-h} \end{bmatrix} \quad (21)$$

we may write the equations (19) and (12b) in the form

$$\tilde{x}_{k+1} = \tilde{A} \tilde{x}_k + \tilde{B} u_k, \quad k \in Z_+ \quad (22a)$$

$$y_k = \tilde{C} \tilde{x}_k + \tilde{D} u_k \quad (22b)$$

where

$$\tilde{A} = \begin{bmatrix} A_\alpha & c_1 I_n & c_2 I_n & \dots & c_{h-1} I_n & c_h I_n \\ I_n & 0 & 0 & \dots & 0 & 0 \\ 0 & I_n & 0 & \dots & 0 & 0 \\ \dots & \dots & \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & \dots & I_n & 0 \end{bmatrix} \in \mathfrak{R}_+^{\tilde{n} \times \tilde{n}}, \quad \tilde{B} = \begin{bmatrix} B \\ 0 \\ \vdots \\ 0 \end{bmatrix} \in \mathfrak{R}_+^{\tilde{n} \times m}$$

$$\tilde{C} = [C \quad 0 \quad \dots \quad 0] \in \mathfrak{R}_+^{p \times \tilde{n}}, \quad \tilde{D} = D \in \mathfrak{R}_+^{p \times m}, \quad \tilde{n} = (1+h)n \quad (22c)$$

To test the practical stability of the positive fractional system (12) the conditions of Theorem 2 can be applied to the system (22).

Theorem 6. The positive fractional system (12) is practically stable if and only if one of the following condition is satisfied

1) Eigenvalues \tilde{z}_k , $k = 1, \dots, \tilde{n}$ of the matrix \tilde{A} have moduli less 1, i.e.

$$|\tilde{z}_k| < 1 \quad \text{for } k = 1, \dots, \tilde{n} \quad (23)$$

- 2) $\det[zI_{\tilde{n}} - \tilde{A}] \neq 0$ for $|z| \geq 1$
3) $\rho(\tilde{A}) < 1$ where $\rho(\tilde{A})$ is the spectral radius defined by $\rho(\tilde{A}) = \max_{1 \leq k \leq \tilde{n}} \{|\tilde{z}_k|\}$ of the matrix \tilde{A}
4) All coefficients \tilde{a}_i , $i = 0, 1, \dots, \tilde{n}-1$ of the characteristic polynomial

$$p_{\tilde{A}}(z) = \det[I_{\tilde{n}}(z+1) - \tilde{A}] = z^{\tilde{n}} + \tilde{a}_{\tilde{n}-1}z^{\tilde{n}-1} + \dots + \tilde{a}_1z + \tilde{a}_0 \quad (24)$$

of the matrix $[I_{\tilde{n}} - \tilde{A}]$ are positive

- 5) All principal minors of the matrix

$$[I_{\tilde{n}} - \tilde{A}] = \begin{bmatrix} \tilde{a}_{11} & \tilde{a}_{12} & \dots & \tilde{a}_{1\tilde{n}} \\ \tilde{a}_{21} & \tilde{a}_{22} & \dots & \tilde{a}_{2\tilde{n}} \\ \dots & \dots & \dots & \dots \\ \tilde{a}_{\tilde{n}1} & \tilde{a}_{\tilde{n}2} & \dots & \tilde{a}_{\tilde{n}\tilde{n}} \end{bmatrix} \quad (25a)$$

are positive, i.e.

$$|\tilde{a}_{11}| > 0, \begin{vmatrix} \tilde{a}_{11} & \tilde{a}_{12} \\ \tilde{a}_{21} & \tilde{a}_{22} \end{vmatrix} > 0, \dots, \det[I_{\tilde{n}} - \tilde{A}] > 0 \quad (25b)$$

- 6) There exist strictly positive vectors $\bar{x}_i \in \mathfrak{R}_+^n$, $i = 0, 1, \dots, h$ satisfying

$$\bar{x}_0 < \bar{x}_1, \bar{x}_1 < \bar{x}_2, \dots, \bar{x}_{h-1} < \bar{x}_h \quad (26a)$$

such that

$$A_\alpha \bar{x}_0 + c_1 \bar{x}_1 + \dots + c_h \bar{x}_h < \bar{x}_0 \quad (26b)$$

Proof. The first five conditions 1)-5) follow immediately from the corresponding conditions of Theorem 2. Using (8) for the matrix \tilde{A} we obtain

$$\begin{bmatrix} A_\alpha & c_1 I_n & c_2 I_n & \dots & c_{h-1} I_n & c_h I_n \\ I_n & 0 & 0 & \dots & 0 & 0 \\ 0 & I_n & 0 & \dots & 0 & 0 \\ \dots & \dots & \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & \dots & I_n & 0 \end{bmatrix} \begin{bmatrix} \bar{x}_0 \\ \bar{x}_1 \\ \bar{x}_2 \\ \vdots \\ \bar{x}_{h-1} \\ \bar{x}_h \end{bmatrix} < \begin{bmatrix} \bar{x}_0 \\ \bar{x}_1 \\ \bar{x}_2 \\ \vdots \\ \bar{x}_{h-1} \\ \bar{x}_h \end{bmatrix} \quad (27)$$

From (27) follow the conditions (26). \square

Theorem 7. The positive fractional system (12) is practically stable if the sum of entries of every row of the adjoint matrix $\text{Adj}[I_{\tilde{n}} - \tilde{A}]$ is strictly positive, i.e.

$$\text{Adj}[I_{\tilde{n}} - \tilde{A}]^{-1} \mathbf{1}_{\tilde{n}} \gg 0 \quad (28)$$

where $\mathbf{1}_{\tilde{n}} = [1 \ 1 \ \dots \ 1]^T \in \mathfrak{R}_+^{\tilde{n}}$, T denotes the transpose.

Proof. It is well-known (Kaczorek 2007c) that if the system (22) is asymptotically stable then

$$\bar{x} = [I_{\tilde{n}} - \tilde{A}]^{-1} \mathbf{1}_{\tilde{n}} \gg 0 \quad (29)$$

is its strictly positive equilibrium point for $\tilde{B}u = \mathbf{1}_{\tilde{n}}$.

Note that

$$\det[I_{\tilde{n}} - \tilde{A}] > 0 \quad (30)$$

since all eigenvalues of the matrix $[I_{\tilde{n}} - \tilde{A}]$ are positive.

The conditions (29) and (30) imply (28). \square

Example 1. Check the practical stability of the positive fractional system

$$\Delta^\alpha x_{k+1} = 0.1x_k, \quad k \in Z_+ \quad (31)$$

for $\alpha = 0.5$ and $h = 2$.

Using (18), (20) and (22c) we obtain

$$c_1 = \frac{\alpha(\alpha-1)}{2} = \frac{1}{8}, \quad c_2 = \frac{1}{16}, \quad a_\alpha = 0.6$$

and

$$\tilde{A} = \begin{bmatrix} a_\alpha & c_1 & c_2 \\ 1 & 0 & 0 \\ 0 & 1 & 0 \end{bmatrix} = \begin{bmatrix} 0.6 & \frac{1}{8} & \frac{1}{16} \\ 1 & 0 & 0 \\ 0 & 1 & 0 \end{bmatrix}$$

In this case the characteristic polynomial (24) has the form

$$p_{\tilde{A}}(z) = \det[I_{\tilde{n}}(z+1) - \tilde{A}] = \begin{vmatrix} z+0.4 & -\frac{1}{8} & -\frac{1}{16} \\ -1 & z+1 & 0 \\ 0 & -1 & z+1 \end{vmatrix} = z^3 + 2.4z^2 + 1.675z + 0.2125 \quad (32)$$

All coefficients of the polynomial (32) are positive and by Theorem 6 the system is practically stable.

Using (28) we obtain

$$\text{Adj}[I_n - \tilde{A}]\mathbf{1}_n = \left(\text{Adj} \begin{bmatrix} 0.4 & -\frac{1}{8} & -\frac{1}{16} \\ -1 & 1 & 0 \\ 0 & -1 & 1 \end{bmatrix} \right) \begin{bmatrix} 1 \\ 1 \\ 1 \end{bmatrix} = \begin{bmatrix} 2.0625 \\ 0.6500 \\ 1.6125 \end{bmatrix}$$

Therefore, by Theorem 7 the system is also practically stable.

Theorem 8. The positive fractional system (12) is practically stable only if the positive system

$$x_{k+1} = A_\alpha x_k, \quad k \in Z_+ \quad (33)$$

is asymptotically stable.

Proof. From (26b) we have

$$(A_\alpha - I_n)\bar{x}_0 + c_1\bar{x}_1 + \dots + c_h\bar{x}_h < 0 \quad (34)$$

Note that the inequality (34) may be satisfied only if there exists a strictly positive vector $\bar{x}_0 \in \mathfrak{R}_+^n$ such that

$$(A_\alpha - I_n)\bar{x}_0 < 0 \quad (35)$$

since $c_1\bar{x}_1 + \dots + c_h\bar{x}_h > 0$.

By Theorem 2 the condition (35) implies the asymptotic stability of the positive system (33). \square

From Theorem 8 we have the following important corollary.

Corollary. The positive fractional system (12) is practically unstable for any finite h if the positive system (33) is asymptotically unstable.

Theorem 9. The positive fractional system (12) is practically unstable if at least one diagonal entry of the matrix A_α is greater than 1.

Proof. The proof follows immediately from Theorems 8 and 3. \square

Example 2. Consider the autonomous positive fractional system described by the equation

$$\Delta^\alpha x_{k+1} = \begin{bmatrix} -0.5 & 1 \\ 2 & 0.5 \end{bmatrix} x_k, \quad k \in Z_+ \quad (36)$$

for $\alpha = 0.8$ and any finite h .

In this case $n = 2$ and

$$A_\alpha = A + I_n \alpha = \begin{bmatrix} 0.3 & 1 \\ 2 & 1.3 \end{bmatrix} \quad (37)$$

By Theorem 9 the positive fractional system is practically unstable for any finite h since the entry (2,2) of the matrix (37) is greater than 1.

The same result follows from the condition 5 of Theorem 2 since the characteristic polynomial of the matrix $A_\alpha - I_n$

$$\begin{aligned} p_{\tilde{A}}(z) &= \det[I_n(z+1) - A_\alpha] = \\ &= \begin{vmatrix} z+0.7 & -1 \\ -2 & z-0.3 \end{vmatrix} = z^2 + 0.4z - 2.21 \end{aligned}$$

has one negative coefficient $\hat{a}_0 = -2.21$.

5. CONCLUDING REMARKS

The new concept (notion) of the practical stability of the positive fractional discrete-time linear systems has been introduced. Necessary and sufficient conditions for the practical stability of the positive fractional systems have been established. It has been shown that the positive fractional system (12) is practically unstable for any finite h if the standard positive system (33) is asymptotically unstable. The considerations have been illustrated by two numerical examples.

The considerations can be easily extended for two-dimensional positive fractional linear systems. An extension of these considerations for continuous-time positive fractional linear systems is an open problem.

ACKNOWLEDGMENTS

This work was supported by Ministry of Science and Higher Education in Poland under work No NNS14 1939 33 and S\WE\1\06.

REFERENCES

- Busłowicz M., 2007. Robust stability of positive discrete-time linear systems with multiple delays with unity rank uncertainty structure or non-negative perturbation matrices, *Bull. Pol. Acad. Techn. Sci.* Vol. 55, No. 1, pp. 347-350.
- Busłowicz M., 2008. Robust stability of convex combination of two fractional degree characteristic polynomials, *Acta Mechanica et Automatica*, (Submitted)
- Farina L., Rinaldi S., 2000. *Positive Linear Systems; Theory and Applications*, J. Wiley, New York.
- Galkowski K., Kummert A., 2005. *Fractional polynomials and nD systems*. Proc IEEE Int. Symp. Circuits and Systems, ISCAS'2005, Kobe, Japan, CD-ROM.
- Kaczorek T., 2002. *Positive 1D and 2D Systems*, Springer-Verlag, London.

- Kaczorek T., 2007a. Reachability and controllability to zero of positive fractional discrete-time systems. *Machine Intelligence and Robotics Control*, vol. 6, no. 4. (in Press)
- Kaczorek T., 2007b. Reachability and controllability to zero of cone fractional linear systems, *Archives of Control Sciences*, vol. 17, no. 3, pp. 357-367.
- Kaczorek T., 2007c. Choice of the forms of Lyapunov functions for positive 2D Roesser model, *Intern. J. Applied Math. and Comp. Sciences*, vol. 17, no. 4, pp. 471-475.
- Kaczorek T., 2008a. Reachability and controllability to zero tests for standard and positive fractional discrete-time systems, *Journal of Automation and System Engineering*, (in Press).
- Kaczorek T., 2008b. Fractional positive continuous-time linear systems and their reachability, *Int. J. Appl. Math. Comput. Sci.*, vol. 18, no. 2 (in Press).
- Kaczorek T., 2008c. Fractional 2D linear systems. *Journal of Automation, Mobile Robotics and Intelligent Systems*, vol.2, no.2.
- Kaczorek T., 2008d. Positive different orders fractional 2D linear systems. *Acta Mechanica et Automatica*, (Submitted).
- Kaczorek T., 2008e. Asymptotic stability of positive 1D and 2D linear systems, *Proc. of National Conference of Automation*, (in Press).
- Kaczorek T., 2008f. LMI approach to stability of 2D positive systems with delays. *Multidimensional Systems and Signal Processing*, vol. 18, no. 3.
- Klamka J., 2002. Positive controllability of positive systems, *Proc. of American Control Conference, ACC-2002, Anchorage, (CD-ROM)*.
- Miller K.S., Ross B., 1993. *An Introduction to the Fractional Calculus and Fractional Differential Equations*. Wiley, New York.
- Nishimoto K., 1984. *Fractional Calculus*. Koriama: DeCartess Press.
- Oldham K. B., Spanier J., 1974. *The Fractional Calculus*. New York: Academmic Press.
- Ortigueira M. D., 1997. Fractional discrete-time linear systems, *Proc. of the IEE-ICASSP 97, Munich, Germany, IEEE, New York*, vol. 3, pp. 2241-2244.
- Ostalczyk P., 2000. The non-integer difference of the discrete-time function and its application to the control system synthesis. *Int. J. Syst, Sci.* vol. 31, no. 12, pp. 551-1561.
- Oustalup A., 1993. *Commande CRONE*. Paris, Hermés.
- Podlubny I., 1999. *Fractional Differential Equations*. San Diego: Academic Press.
- Sierociuk D., Dzieliński D., 2006. Fractional Kalman filter algorithm for the states, parameters and order of fractional system estimation. *Int. J. Appl. Math. Comp. Sci.*, vol. 16, no. 1, pp. 129-140.
- Vinagre M., Feliu V., 2002. Modeling and control of dynamic system using fractional calculus: Application to electrochemical processes and flexible structures. *Proc. 41st IEEE Conf. Decision and Control, Las Vegas, NV*, pp. 214-239.
- Twardy M., 2007. An LMI approach to checking stability of 2D positive systems, *Bull. Pol. Acad. Techn. Sci.* vol. 55, no.4, pp. 379-383.
- Twardy M., 2007. On the alternative stability criteria for positive systems, *Bull. Pol. Acad. Techn. Sci.* vol. 55, no.4, pp. 385-393.

AUTHOR BIOGRAPHY

TADEUSZ KACZOREK, born on 27 April 1932 in Poland, received the MSc, PhD and DSc degrees from Electrical Engineering of Warsaw University of Technology in 1956, 1962 and 1964, respectively. In the period 1968-69 he has the dean of Electrical Engineering Faculty and in the period 1970-73 he was the prorector of Warsaw University of Technology. Since 1971 he has been professor and since 1974 full professor at Warsaw University of Technology. In 1986 he was elected a corresp. member and in 1996 full member of Polish Academy of Sciences. In the period 1988-1991 he was the director of the Research Centre of Polish Academy of Sciences in Rome. In May 2004 he was elected the honorary member of the Hungariar Academy of Sciences. He was awarded by the title doctor honoris causa by the University of Zielona Góra (2002), the Technical University of Lublin (2004), the Technical University of Szczecin (2004) and Warsaw University of Technology (2004). His research interests cover the theory of systems and the automatic control systems theory, specially, singular multidimensional systems, positive multidimensional systems and singular positive 1D and 2D systems. He has initiated the research in the field of singular 2D and positive 2D systems. He has published 21 books (six in English) and over 800 scientific papers. He supervised 65 PhD theses. He is Editor-in-Chief of Bulletin of Polish Academy of Scences, Technology Sciences and Editorial Member of about ten international journals. Tadeusz Kaczorek can be contacted at: kaczorek@isep.pw.edu.pl